

KW	HP	MONOFASICOS		TRIFASICOS (4 polos 50 y 60Hz)			
		220 V	240 V	220 V	230 V	380 V	400 V
0,37	0,5	3,9	3,6	1,8	1,7	1,04	0,9
0,55	0,75	5,2	4,8	2,5	2,4	1,5	1,4
0,75	1,0	6,6	6,1	3,4	3,2	2,0	1,9
1,2	1,5	9,6	8,8	4,5	4,3	2,6	2,5
1,5	2,0	12,7	11,7	6,1	5,8	3,5	3,5
1,8	2,5	15,7	14,4
2,2	3,0	18,6	17,1	8,8	8,4	5,1	4,8
3,0	4,0	24,3	22,2	11,4	10,9	6,6	6,3
3,5	5,0	29,6	27,1
3,7	5,0	14,0	13,3	8,0	7,6
4,0	5,5	14,8	14,1	8,6	8,1
4,4	6,0	34,7	31,8
5,2	7,0	39,8	36,5
5,5	7,5	42,2	38,7	20,0	19,0	11,7	11,1
6,0	8,0	44,5	40,8
6,7	9,0	49,5	45,4
7,5	10,0	54,4	50,0	27,0	25,8	15,5	14,7
9,0	12,0	32,0	30,6	18,7	17,7
10,0	13,5	36,0	34,4	20,5	19,5
11,0	15,0	38,0	36,8	22,0	20,9
15,0	20,0	52,0	50,2	30,0	28,5
18,5	25,0	64,0	61,2	37,0	35,1
22,0	30,0	76,0	72,6	44,0	42,0
25,0	34,0	86,0	82,2	50,0	47,5
30,0	40,0	102,0	97,5	59,0	56,0
33,0	45,0	112,0	107,0	65,0	62,0
37,0	50,0	124,0	119,0	72,0	68,4
40,0	54,0	133,0	127,0	77,0	73,0
45,0	60,0	146,0	140,0	85,0	81,0
51,0	70,0	167,0	160,0	97,0	92,0
55,0	75,0	179,0	171,0	104,0	99,0
59,0	80,0	192,0	184,0	111,0	105,0
63,0	85,0	204,0	195,0	118,0	112,0
75,0	100,0	240,0	230,0	139,0	132,0
80,0	110,0	257,0	246,0	149,0	141,0
92,0	125,0	295,0	282,0	171,0	162,0